

08/23/00



JC913 U.S. PTO

08-28-00

A

+



08/23/00

PTO/SB/05 (2/98) (modified)

Approved for use through 9/30/2000, OMB 0651-0032

Patent and Trademark Office: U.S. DEPARTMENT OF COMMERCE

<b>NEW UTILITY PATENT APPLICATION TRANSMITTAL</b> <i>(only for new nonprovisional applications under 37 CFR 1.53(b))</i>	Attorney Docket Number	5036
	First Named Inventor	Stewart Kevin Hester
	Total Pages in this Submission	72
	Express Mail Label No.	EL482477909US

JC913 U.S. PTO  
09/648672

APPLICATION ELEMENTS	ACCOMPANYING APPLICATION PARTS
1. <input checked="" type="checkbox"/> Fee Transmittal Form (in duplicate) <input type="checkbox"/> Check Enclosed	6. <input checked="" type="checkbox"/> Assignment & Assignment Recordation Cover Sheet
2. <input checked="" type="checkbox"/> Specification <i>(preferred arrangement set forth below)</i> <ul style="list-style-type: none"><li><input checked="" type="checkbox"/> Descriptive Title of the Invention</li><li><input checked="" type="checkbox"/> Cross Reference(s) to Related Case(s)</li><li><input checked="" type="checkbox"/> Statement Regarding Fed sponsored R &amp; D</li><li><input checked="" type="checkbox"/> Background of the Invention</li><li><input checked="" type="checkbox"/> Brief Summary of the Invention</li><li><input checked="" type="checkbox"/> Brief Description of the Drawing(s)</li><li><input checked="" type="checkbox"/> Detailed Description</li><li><input checked="" type="checkbox"/> Claim or Claims</li><li><input checked="" type="checkbox"/> Abstract of the Disclosure</li></ul>	7. <input type="checkbox"/> Certified Copy of Priority Document(s) <i>(if foreign priority is claimed)</i>
3. <input checked="" type="checkbox"/> Drawing(s) <i>(when necessary per 35 USC 113)</i>	8. <input type="checkbox"/> Information Disclosure Statement & PTO-1449 <input type="checkbox"/> Copies of IDS Citation(s)
4. Oath or Declaration <ul style="list-style-type: none"><li>a. <input checked="" type="checkbox"/> New Declaration <input checked="" type="checkbox"/> Executed</li><li>b. <input type="checkbox"/> Copy from a prior application (37 CFR 1.63(d)) <i>(for continuation/divisional with Box 17 completed)</i><ul style="list-style-type: none"><li>i. <input type="checkbox"/> DELETION OF INVENTOR(S) Signed statement attached deleting inventor(s) named in the prior application, see 37 CFR 1.63(d)(2) and 1.33(b).</li></ul></li></ul>	9. <input type="checkbox"/> Preliminary Amendment
5. <input type="checkbox"/> Incorporation by Reference <i>(useable if Box 4b is checked)</i> . The entire disclosure of the prior application, from which a copy of the oath or declaration is supplied under Box 4b, is considered as being part of the disclosure of the accompanying application and is hereby incorporated by reference therein.	10. Small Entity Statement  <input checked="" type="checkbox"/> New Statement enclosed <input type="checkbox"/> Statement filed in prior application. Status still proper and desired
	11. <input checked="" type="checkbox"/> Return Postcard
	12. <input type="checkbox"/> _____
	13. <input type="checkbox"/> _____
	14. <input type="checkbox"/> _____
	15. <input type="checkbox"/> _____
	16. <input type="checkbox"/> _____
	<b>ADDRESS TO:</b> <b>Box Patent Application</b> <b>Commissioner for Patents</b> <b>Washington, D.C. 20231</b>

17. If a CONTINUING APPLICATION, check appropriate box and supply the requisite information below and in a preliminary amendment:

☐ Continuation ☐ Divisional ☐ Continuation-in-part (CIP) of prior application No: \_\_\_\_/\_\_\_\_

Prior application information: Examiner: \_\_\_\_\_ Group/Art Unit: \_\_\_\_\_

## 18. CORRESPONDENCE ADDRESS

NAME	Edward A. Van Gieson Fenwick & West LLP				
ADDRESS	Two Palo Alto Square				
CITY	Palo Alto	STATE	CA	ZIP CODE	94306
COUNTRY	U.S.A.	TELEPHONE	(650) 858-7997	FAX	(650) 494-1417
Name (Print/Type)	Edward A. Van Gieson			Registration No. (Attorney/Agent)	44,386
Signature	Edward Van Gieson			Date	August 23, 2000

21216/05036/DOCS/1084026.1

**VERIFIED STATEMENT CLAIMING SMALL ENTITY STATUS**  
**(37 CFR 1.9(f) & 1.27(e))--SMALL BUSINESS CONCERN**

Docket Number (Optional):  
**5036**

Applicant or Patentee: Stewart Kevin Hester, Todd Beine, Rainer Robert Iraschko, Kent Wilfred George Ryhorchuk

Application or Patent No.: \_\_\_\_\_

Filing Date or Issue Date: \_\_\_\_\_

Title: **FAULT DETECTION AND ISOLATION IN AN OPTICAL NETWORK**

I hereby declare that I am

☐ the owner of the small business concern identified below:

☒ an official of the small business concern empowered to act on behalf of the concern identified below:

NAME OF SMALL BUSINESS CONCERN ONI Systems Corp.

ADDRESS OF SMALL BUSINESS CONCERN 166 Baypointe Parkway

San Jose, CA 95134-1621

I hereby declare that the above identified small business concern qualifies as a small business concern as defined in 13 CFR 121.12, and reproduced in 37 CFR 1.9(d), for purposes of paying reduced fees to the United States Patent and Trademark Office, in that the number of employees of the concern, including those of its affiliates, does not exceed 500 persons. For purposes of this statement, (1) the number of employees of the business concern is the average over the previous fiscal year of the concern of the persons employed on a full-time, part-time or temporary basis during each of the pay periods of the fiscal year, and (2) concerns are affiliates of each other when either, directly or indirectly, one concern controls or has the power to control the other, or a third party or parties controls or has the power to control both.

I hereby declare that rights under contract or law have been conveyed to and remain with the small business concern identified above with regard to the invention described in:

☒ the specification filed herewith with title as listed above.

☐ the application identified above.

☐ the patent identified above.

If the rights held by the above identified small business concern are not exclusive, each individual, concern or organization having rights in the invention must file separate verified statements averring to their status as small entities, and no rights to the invention are held by any person, other than the inventor, who would not qualify as an independent inventor under 37CFR 1.9(c) if that person made the invention, or by any concern which would not qualify as a small business concern under 37 CFR 1.9(d), or a nonprofit organization under 37 CFR 1.9(e).

Each such person, concern or organization having any rights in the invention is listed below:

☒ No such person, concern, or organization exists.

☐ Each such person, concern or organization is listed below:

Separate verified statements are required from each named person, concern or organization having rights to the invention averring to their status as small entities. (37 CFR 1.27)

I acknowledge the duty to file, in this application or patent, notification of any change in status resulting in loss of entitlement to small entity status prior to paying, or at the time of paying, the earliest of the issue fee or any maintenance fee due after the date on which status as a small entity is no longer appropriate. (37 CFR 1.28(b))

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under section 1001 of Title 18 of the United States Code, and that such willful false statements may jeopardize the validity of the application, any patent issuing thereon, or any patent to which this verified statement is directed.

NAME OF PERSON SIGNING Mike Dillon

TITLE OF PERSON IF OTHER THAN OWNER VP & General Counsel

ADDRESS OF PERSON SIGNING 166 Baypointe Parkway, San Jose, CA 95134-1621

SIGNATURE \_\_\_\_\_

DATE August 22, 2000

09:23:23 "2494950

## **FAULT DETECTION AND ISOLATION IN AN OPTICAL NETWORK**

Prepared By:  
Edward Vangieson, Reg. No. 44,386  
Fenwick & West LLP  
2 Palo Alto Square  
Palo Alto, CA 94306  
650.494.0600

Filed On: August 23, 2000

Express Mail No: EL482477909US

## FAULT DETECTION AND ISOLATION IN AN OPTICAL NETWORK

### RELATED APPLICATIONS

This application claims the benefit of U.S. provisional application serial number 60/152,138, "Fault Detection And Isolation In An Optical Network," by inventors Kevin  
5 Hester, Todd Beine, Rainer Iraschko, and Kent Rhyorchuk, filed August 24, 1999, the  
entire contents of which are hereby incorporated by reference.

### BACKGROUND OF THE INVENTION

#### 1. Field of the Invention

The present invention relates generally to fault detection and fault isolation in an  
10 optical network.

#### 2. Description of Background Art

Optical data networks typically include a plurality of nodes linked by optical  
fibers into a network. The network may be one of several common topologies, such as a  
linear chain network, an optical star network, or an optical ring network. Optical  
15 networks are also classified by the geographic size of the network, with wide area  
networks (WANs) and metropolitan area networks (MANs) being of increasing interest  
for providing high bandwidth network data links to and from corporations and LAN  
campuses, for example.

A popular optical network topology for MANs is an optical ring. As shown in FIG. 1, an optical ring network 100 typically comprises a sequence of network nodes 105, at least one primary optical fiber path 110, commonly known as “working fiber” coupling data between the nodes. Optical networks transport large flows of information such that system outages of even a few seconds can cause the loss of huge quantities of information. This is especially true for wavelength division multiplexing (WDM) and dense wavelength division multiplexing (DWDM) optical networks, which simultaneously transmit data in a plurality of optical channels, with each channel comprising a different optical wavelength.

The reliability of an optical network is an important design consideration. Optical networks can fail due to several different mechanisms. Line failure is commonly defined as a fault in the ability of light to be transmitted between nodes along a working fiber, i.e., there is no light coupled into the node because of damage to the optical fiber. Additionally, a line failure can occur at or near the interface of the fiber and a node. For example, the optical fiber may not be properly inserted into the node. Additionally, a failure of an optical interface element may be optically equivalent to a line fault if it results in a total loss of signal at all channel wavelengths to all downstream components. For example, a fault in the optical interface element receiving signals from the fiber that results in a complete loss of signal to all subsequent optical elements within the node is equivalent in effect to a fault in the fiber. An electrical equipment failure is commonly defined as a failure in one or more electrical or electro-optic modules in the node. These include optical amplifiers, multiplexors/demultiplexors, transponders, and other elements used to amplify, frequency shift, or to add or drop individual channels or bands. An

electrical equipment failure may result in a loss in all channels, but may more commonly result in only a limited number of channels being dropped.

Optical networks typically employ several different approaches to permit network service to be rapidly restored in the event of a fault. Referring again to FIG. 1, optical ring networks typically include at least one protection fiber 115 between each node 105. The protection fiber 115 provides an alternate path for optical data in case the primary optical fiber 110 becomes broken or damaged along a portion of its length. Additionally, the protection fiber facilitates the routing of data to bypass a defective node 105 via a path in the protection fiber. In the case of a unidirectional path-switched ring (UPSR) the working fiber and the protection fiber commonly carry information in opposite directions, e.g., data is commonly transmitted in the working fiber in a clockwise direction and in the protection fiber in the counter-clockwise direction. Bidirectional path switched rings (BPSR) permit traffic along the ring to be carried in both directions via two or more working fibers and two or more protection fibers.

FIG. 2 is an illustrative diagram of a UPSR ring 200 operating with working and protection fiber path links intact. For the purposes of illustration, an optical data path is shown between the tributary interfaces of two nodes, NE1 and NE2. As shown in FIG. 3, in the event of a fiber break the working traffic is switched to the protection fiber in order to maintain the data link between the tributary interfaces of nodes NE1 and NE2. This is performed using optical line switching elements (not shown in FIGS. 2 and 3) within a node in order to optically switch the path of the optical signals. Note that a complete failure of one or more electrical elements within node NE1 or NE2 could also break the flow of data. Consequently, nodes NE1 and NE2 typically include redundant electrical

and electro-optic elements that can be switched into use in the event that one or more electrical elements in the node fails. This is commonly known as equipment switching.

As shown in FIG. 1, a network management system (NMS) 120 is typically used to regulate the action of the nodes 105 in the event of a line failure or an equipment failure in order to restore network service. The NMS 120 typically comprises a central workstation computer receiving electrical signals corresponding to the optical strength of every optical channel transmitted through each active line of each node. The NMS 120 is typically programmed with a list of rules or procedures for handling different types of failures. Multi-channel optical-to-electrical-to-optical (OEO) detectors (not shown in FIGS. 1-3) in each node can be used to measure the signal strength of each channel entering or leaving the node. This permits the NMS 120 to determine if a channel has been dropped. If the NMS 120 determines that a channel has been dropped in a particular node, the NMS may instruct the node to perform an equipment switch of a component in the path of the dropped channel likely to have failed. The NMS 120 monitors the activity of all of the nodes, determines if a change in traffic occurs, makes a decision whether a line fault of equipment fault has occurred, isolates the fault to a particular node or fiber path, and issues appropriate commands to all of the nodes to perform one or more equipment switches or line switches to restore network traffic.

While the network management system shown in FIG. 1 improves the reliability of network 100, the inventors of the present application have recognized that it has several substantial drawbacks, particularly in regards to high performance metropolitan area networks. First, it can take a significant length of time for a central computer of a NMS 120 to determine an appropriate course of action due to the cumulative time delays

of the system. There are finite response times for each OEO to measure the signal strengths of each optical channel to determine if a channel is dropped. There is also a significant propagation time for channel status signals to reach the central computer of NMS 120. This propagation time includes the time delay for short-haul Ethernet cables coupled to the node along with the time delays of the long-haul data link (e.g., a telephone line) to the central computer, which may be located several kilometers away from an individual node in network 100. There is also a time period required for the central computer to assess the state of each node and to make a decision. Still yet another time period is associated with the time delay required to transmit control signals from the central computer of NMS 120 back to each node via Ethernet and long-haul connections. There is also a time delay associated with the circuitry at the node that is used to implement a line switch or an equipment switch. In a conventional MAN system 100 the total elapsed time between the detection of a failure and a line switch or equipment switch being implemented can exceed 0.1 seconds. One industry standard that has evolved is that a communication disruption lasting more than 50 milliseconds constitutes a network outage, i.e., tributary networks receiving and transmitting data via network 100 are designed upon the assumption that optical network 100 has outages of less than 50 milliseconds. Network outages in excess of 0.1 seconds may therefore cause an irreparable loss of data to a tributary network.

Another drawback of network 100 is that the NMS 120 can be comparatively expensive to implement. The central computer is often implemented as a high performance work station, which is comparatively expensive. Another substantial cost is associated with the OEO modules used to measure channel strength in each node 105. OEO modules increase with cost as a function of the number of optical channels that they



are capable of analyzing. Additionally, the cost of each OEO module tends to increase with the data capacity of each channel since faster optical and electrical components are required for high data rate channels. Advances in DWDM technology now permit thirty or more high data-rate channels to be implemented in an OEO module. This results in a  
5 corresponding increase in the cost of the OEO modules compared with first generation WDM designs having three to five moderate data-rate channels.

Another drawback of network 100 is that it may provide insufficient information to isolate electrical equipment failures for later repair. The increase in the number of channels in DWDM systems has led to multistage node designs having several stages.  
10 The stages commonly include various combinations of band pass filters, channel filters, wavelength shifters, optical amplifiers, multiplexors, and demultiplexors. Each stage, in turn, may host one channel, several channels, most of the channels, all of the channels, or frequency shifted versions of the channels, depending upon the function of the stage. A single OEO module is typically insufficient to determine the element within a node that  
15 has dropped a channel. Consequently, several OEO modules may be required for fault isolation, further increasing the cost of the system.

Therefore, there is a need for an improved system and method for performing fault detection, isolation, and network restoration in an optical network.

#### SUMMARY OF THE INVENTION

20 The present invention generally comprises a fault detection and isolation system and method for optical networks. One aspect of the present invention is that a local controller in each node makes decisions on whether to activate fault restoration elements

within the node, eliminating the need for a central computer to coordinate the actions of each node in response to a fault.

Generally speaking, an embodiment of an optical node of the present invention generally comprises at least one fault restoration element for restoring network traffic in response to a fault; at least one optical sensor coupled to the node for measuring a first set of optical characteristics of the optical channels coupled to the node; a signal sensor for receiving data from another device corresponding to a second set of optical characteristics of the optical channels; and a controller for adjusting the operation of said at least one restoration element as a function of said first and said second set of optical characteristics, whereby said controller determines a network fault requiring local action and directs said at least one restoration element to perform a restoration instance. In preferred embodiments the fault restoration element may include a line switcher, a redundant electrical or electro-optic element, or a combination of a line switcher and redundant electrical or electro-optic element. In one embodiment the controller is a microprocessor having a software program residing on the microprocessor that includes a problem list for correlating the occurrence of potential faults from the first and second set of optical characteristics. In a preferred embodiment the signal sensor is a transceiver for communicating channel status messages with a neighboring node via an optical channel.

Broadly speaking, the present invention also includes methods of fault detection and isolation. One embodiment is for an optical network having a plurality of optical nodes, each node including at least one local optical sensor for measuring optical characteristics of the datastream at the local node, at least one transceiver for communicating data to each neighboring node that it is coupled to via a fiber optic link,

and each node having a local controller for controlling at least one local restoration element, the method comprising the steps of: sensing a set of optical characteristics of the datastream at each node; updating a channel map of active channels at each node of the optical network; and communicating the updated channel map to the nodes via the fiber optic link; wherein each local controller compares the optical characteristics measured at  
5 the local node to the channel map to determine if a fault has occurred requiring that the local controller activate a restoration element.

The method of the present invention may be practiced with nodes having fault restoration elements that include line switchers, redundant electrical or electro-optic  
10 elements, and combinations thereof. In one embodiment the method of fault detection and isolation is for a node of an optical network having a datastream with a plurality of optical channels, the network including a plurality of nodes coupled to each neighboring node, each node having at least one local optical sensor, each node having at least one optical transceiver for communicating status reports to each neighboring node that it is  
15 optically coupled to, and each node having a local controller for controlling a local line switcher residing in the node, the method comprising the steps of: sensing a loss in signal from a neighboring node via the local optical sensor; monitoring the transceiver to determine if the neighboring node is communicating status reports to the node; and initiating a line switch to redirect traffic to an alternate optical path to restore data traffic  
20 if there is a loss in signal from the neighboring node and status reports are not being receiving from the neighboring node. In another embodiment the method of fault detection and isolation is for a node of an optical network having an optical datastream with a plurality of channels, the network including a plurality of nodes optically coupled to each neighboring node, each node having at least one local optical sensor, at least one  
25 transceiver for communicating data to each neighboring node that it is coupled to, and a local controller for controlling redundant elements residing in the node, the method

comprising the steps of: sensing a first set of optical characteristics of the optical channels traversing the node; receiving status reports that include a second set of optical characteristics of the optical channels measured by at least one sensor in another node of the network; comparing the first and second set of optical characteristics; determining if one or more optical channels are being dropped in the node; and initiating an equipment switch in the local node to restore the dropped traffic.

### BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram of a prior art optical network having a central network management system for detecting faults and restoring network traffic.

FIG. 2 is a block diagram of a prior art optical ring network having a central network management system controlling traffic between working fibers and protection fibers.

FIG. 3 is a prior art block diagram of the network of FIG. 2 showing how the central network management system redirects traffic in response to a line fault.

FIG. 4 is a block diagram of an embodiment of optical network in accordance with the present invention.

FIG. 5 is a block diagram of an embodiment of an optical network in accordance with the present invention.

FIG. 6 is a block diagram showing a preferred arrangement of multiplexing/demultiplexing elements within the nodes of a wavelength division multiplexing optical network in accordance with the present invention.

FIG. 7 is a functional block diagram showing a preferred node arrangement in  
5 accordance with the present invention.

FIG. 8 is a block diagram of a preferred embodiment of the node of FIG. 7.

FIG. 9 shows an embodiment having node components arranged on field replaceable circuit packs communicatively coupled to processor and memory modules.

FIGS. 10A and 10 B are portions of an exemplary decision table used to detect  
10 and isolate faults in a ring network.

FIG. 11 is a functional block diagram of a fault detection and isolation controller system in accordance with the present invention.

FIG. 12 is an interaction diagram showing a preferred sequence of steps for initiating an equipment switch instance.

FIG. 13 is an interaction diagram showing a preferred sequence of steps for  
15 initiating a line switch instance.

#### **DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS**

The figures depict a preferred embodiment of the present invention for purposes of illustration only. One of skill in the art will readily recognize from the following

discussion that alternative embodiments of the structures and methods disclosed herein may be employed without departing from the principles of the claimed invention.

FIG. 4 is a block diagram of a portion of an optical network 400 illustrating some of the general principles of the present invention. For the purposes of illustration many conventional elements used in optical networks are omitted. It will also be understood that optical network 400 may be part of a larger chain, branched chain, mesh, or ring network. A plurality of network optical nodes 405 are shown coupled by fiber spans 410. The fiber spans 410 may comprise one or more optical fiber lines that include all of the potential optical channel data links between neighboring nodes for communicating an optical datastream. For the purposes of illustration, the optical paths in the fiber lines are shown by arrows, although it will be understood that the drawing is not to scale and that each arrow corresponds to at least one fiber coupled to corresponding optical ports 460 at each node. As described below in more detail, in a preferred embodiment node 405 has a plurality of ports arranged to that a line switcher may be used to redirect the optical data stream to an alternate output port in the even of a line fault. For example a fiber span 410 may comprise a working fiber line and a protection fiber line each coupled to a node by respective ports. In a preferred embodiment for wavelength division multiplexing, each fiber line comprises a single spatial-mode optical fiber capable of transmitting a plurality of optical wavelengths.

Each node 405 includes its own local restoration elements 420 to restore network service in the event of a fault that could disrupt network traffic. The restoration elements 420 preferably include a line switcher responsive to a line switch command to re-direct traffic away from a faulty line of a span 410 and onto an alternate line by selecting an

alternate optical pathway between two ports of the node, i.e. changing the port from which the data stream exits the node such that the datastream is redirected onto an alternate line. The restoration elements also preferably include redundant electrical or electro-optic elements response to an equipment switch command to maintain network traffic in the event of a failure of an electrical or electro-optic component. Examples of redundant electro-optic elements include but are not limited to: redundant band pass filters, redundant channel filters, redundant multiplexors, redundant demultiplexors, redundant optical detectors, redundant optical amplifiers, or redundant transponders. It will be understood that while there is at least one fault restoration element 420 that various combinations of fault restorations elements may be included depending upon the particular application. Each node has its own local controller 430 that determines if a fault has occurred and that regulates the actions of the restoration elements 420 within the node.

An individual controller 430 may use several different sources of information to make a decision whether to activate the restoration elements 420 of its node. First, each node 405 includes at least one internal optical sensor 418 for measuring a first set of optical characteristics of the optical channels at the node. The first set of optical characteristics corresponds to information on channel activity that may be determined by the optical sensors at the local node, such as information regarding a complete loss of signal (LOS) in a single channel, a band of channels, or all the channels, depending upon the resolution of the sensor and the number of channels received by the sensor. The optical sensor 418 may be part of a pre-amplification or post-amplification component of the node. Additionally, each node 405 may also include other internal elements, such as p-I-n photodiodes, configured to provide information on the signal strength of individual

channels or bands of channels. P-I-N photodiodes are a type of photodetector that has a lightly doped intrinsic semiconductor sandwiched between p-type and n-type semiconductors. However, optical sensors, such as p-I-n detectors, that are not otherwise required to perform a necessary node function (e.g., multiplexing or demultiplexing) increase the cost of network 400 and introduce extra signal loss that must be compensated for with optical amplifiers. Consequently, it is desirable to use optical sensors required for other functions to provide information on the characteristics of the optical channels. For example, some types of transponders include an inherent sensing capability that may be used to provide information on the characteristics of the optical channels (e.g., the presence of optical power in a channel received by the transponder). The required resolution of an optical sensor 418 depends upon whether the sensor is coupled to a single channel, band of channels (e.g., three channels), or to all of the channels. Conventional p-I-n optical detectors commonly have sufficient resolution to measure the loss of a single channel from a band having a small number of channels (e.g., a band having three to five channels), but commonly lack sufficient resolution to determine if a single channel has been dropped from a large number of channels, such as when thirty optical channels are coupled to a p-I-n detector.

Second, in a preferred embodiment each node receives information from at least one other element, such as an upstream element in a unidirectional path switched response (UPSR) optical ring. This information from the upstream element assists the node to determine if individual channels or bands of channels have been dropped (lost) prior to entering the node. In a preferred embodiment, each node receives status information from upstream nodes from an optical supervisory channel (OSC) communicated by the optical span. This status information preferably includes the



information that at least one upstream controller has measured or otherwise collected regarding the status of the network channels. The status information may include a second set of characteristics for the channels upstream of the node along with other network status information. The second set of optical characteristics may, for example, include information on channel activity measured at the upstream node. Additionally, the second set of optical characteristics may also include a channel map of channel activity of a plurality of nodes. For example, referring to FIG. 4, node 2 may record a set of characteristics for the optical channels traversing node 2 using its own optical sensors and transmit this information to node 1 via the OSC. Node 2 may, for example, communicate to node 1 that it is receiving optical signals (e.g., from node 3) or that some of its transponders or other optical detectors have experienced a loss of power in one or more channels or bands of channels. Additionally, node 2 may relay to node 1 messages that include network status information that it has received from other nodes. For example, the messages transmitted via the OSC channel may, for example, include a channel map of active channels that is updated and forwarded at each node as it is passed along to downstream nodes. Additionally, the OSC channel may be used by a node to transmit status and alert messages that are also forwarded to other nodes of the network.

The OSC channel also permits the nodes to communicate messages on planned restoration events to each other, thereby permitting the nodes to coordinate their actions. For example, node 2 may send a signal announcing to its neighbors that it is about to initiate an equipment switch that will cause a short disruption in traffic through node 2. This information will alert node 1 to not interpret a short disruption in upstream traffic as a line fault. Additionally, the OSC channel permits the nodes to share information on the results of a restoration event. For example, if node 2 initiates an equipment switch that is

unsuccessful in restoring network traffic then node 2 can communicate this information to the other nodes as a failed restoration instance message. This may provide information to another node that enables that node to determine if an equipment switch is necessary at that node. This so-called "rolling equipment switch" mode of restoration is made possible by each node sharing data on the results of an equipment switch with its neighbors. The OSC channel thus provides a means for the nodes to communicate a variety of status information, including channel status and coordination information.

In an alternate embodiment, an optical analyzer 440, such as an optical spectrum analyzer (OSA) may be used to measure information on the channel activity and communicate it to a node 405. This information may include information on the number of optical channels transmitted along the fiber to the optical analyzer. Additionally, other information may also be recorded, such as information on channel width (Hz) or other information indicative of a failure of a laser, amplifier, or electro-optic component in a network node. As shown in FIG. 4, the OSA 440 may be electrically coupled via electrical connections 445 to a signal sensor 447 of a downstream node if the OSA is disposed a comparatively short distance from the node. However, if the OSA is located a substantial distance upstream of the node it may be desirable to communicatively couple the OSA to the downstream node using an optical data channel of the fiber span, i.e. an optical sensor 418 is used to perform the function of the signal sensor.

One advantage of optical network 400 is that each node 405 benefits from the optical channel information of other devices, particularly upstream nodes. This means that an individual node 405 requires comparatively fewer internal optical sensors (e.g., P-I-N photodetectors) in order to have the capability to detect and isolate an equipment

fault. Additionally, each individual node 405 receives information from its neighboring nodes that allows it to determine if a line fault has occurred between it and its neighboring node, thus enabling the node to make a decision whether a line switch is appropriate.

5 Another benefit of network 400 is that it eliminates the need for centralized control of network restoration. Node controller 430 may be implemented as a comparatively low cost control module. For example, node controller 430 may be a local computer, microcomputer, microprocessor, microcontroller, or dedicated circuit  
10 configured to control the actions of the restoration elements within the node that it resides. In a preferred embodiment, node controller 430 is a comparatively inexpensive microprocessor programmed to act as a local computer that controls the actions of the restoration elements 420 within the node that it resides.

The use of a local controller 430 at each optical node 405 results in fast response times compared to a conventional centralized NMS system 100. There are currently two  
15 important restoration time standards in the industry for a maximum acceptable interruption in network traffic. These restoration time standards correspond to a fifty millisecond standard and also a one hundred millisecond standard developed by BELLCORE. Estimates by the inventors indicate that a metropolitan area network having a ring topology constructed in accord with the teachings of the present invention  
20 can restore line faults in a time period less than either common industry standard, i.e., less than either one hundred milliseconds or fifty milliseconds. This is in contrast to a conventional optical network 100 having a central NMS 120, which may require up to one second to restore traffic after a line failure in a metropolitan area network.

FIG. 5 is block diagram of a generalized representation of two neighboring nodes of an optical network 500 coupled by an optical span 510. As shown in FIG. 5, an optical signal sensor 520 (e.g., a P-I-N photodetector) is used to convert the OSC optical channel into an electrical signal (i.e., optical to electrical conversion of the OSC channel). The OSC channel is preferably tapped off using an optical filter or demultiplexor disposed in a line card element. A microprocessor controller 530 is preferably used to host a fault detection and isolation computer program at each node. The fault detection and isolation program correlates available information on optical channel characteristics in the node with status information received from neighboring nodes to detect changes in channel activity indicative of a line fault or equipment fault in the node. The program preferably includes a decision table or algorithm to determine if a line switch or equipment switch is required. As shown in FIG. 5, a line switcher 525 is preferably included to redirect optical traffic to the port of an alternate optical line in the event of a line failure. A wavelength division multiplexing (WDM) optical network typically includes electro-optic elements 530 such as multiplexors, demultiplexors, and optical filters. A set of redundant electro-optical elements 535, R, is preferably also included to permit an equipment switch. Each node may also include a transponder 540 to convert the channels into an optical frequency or format appropriate for a tributary network coupled to the node. In some cases the transponder includes optical power level capability, i.e., the frequency or format conversion performed by the transponder inherently involves determining that the channel is active. FIG. 6 is a block diagram illustrating a preferred arrangement of band filters, channel filters, and wavelength conversion transponders for an optical ring network. For the purposes of illustration, the line switcher, controller, and redundant elements are not shown in FIG. 6.

FIG. 7 is a block diagram of a preferred node structure 700 for an optical ring network. The functional attributes of each block are also shown. It will be understood that many variations on the structural and functional relationship of node 700 are encompassed by the present invention.

5 As shown in FIG. 7, in a preferred node structure 700 a control section 710 includes a configuration database, operational interfaces, and software modules for inter-node communications via OSC channels. The common control section provides software administration and control of the node and preferably includes a PC compatible processor element module and persistent storage module. The processor element module preferably  
10 runs an Embedded WINDOWS NT operating system.

The transport section 720 includes elements for line amplification, a line switcher, measuring the OSC signal, and transmitting or terminating (if desired) a line. The transport section 720 is configured to receive four ports corresponding to two West-line ports and two East-line ports, in accord with standard terminology in UPSR and BLSR  
15 rings that a first span comprising a working fiber and a protection fiber are coupled via two ports 722, 724 to one side of transport section 720 whereas a second span including another working fiber and protection fiber are coupled via ports 726, 728 to the other side of transport section 720. The transport section terminates the spans between nodes. It divides the received optical signal into working, protection, and un-switched band groups  
20 and provides protection switching in BLSR and UPSR systems. It preferably includes an optical amplifier such as an Erbium doped fiber amplifier to boost optical DWDM transmission levels.

The multiplex section 730 includes electro-optic elements for performing wavelength division multiplexing operations and has redundant elements for equipment protection. The multiplex section 730 is preferably implemented as a two-stage optical multiplexor that aggregates signals from the tributary section 740 into the line side DWDM format and splits received line-side signals into the individual channels used by the tributary section. The first multiplex stage combines the individual channels launched by the tributary transponder wavelength converter interfaces (WCIs) into three-channel wide bands. Each band is preferably fed into the aggregated line-side signal by a band wavelength division multiplexor (BWDM) in the second stage. The BWDMs multiplex (add) and demultiplex (drop) groups of three wavelengths for further subdivision by channel wavelength division multiplexors (CWDM)s. The CWDM modules multiplex a set of three outgoing wavelengths into a band and demultiplex the corresponding incoming band of wavelengths into three individual channels. CWDMs also switch traffic between the primary BWDM CP backup BWDM modules in redundant applications. In a protection switching configuration, a signal carried on a working band is restored by switching it to the equivalent protect band on the other fiber.

The tributary section 740 includes transponders (WCIs) for wavelength translation, tributary network ports 745, and has add/drop signal routing capability. The tributary section is the point of connection for client optical signals and it converts the line side DWDM frequencies into short reach signals, such as 850 nm and 1310 nm signals. Each WCI of the tributary section has two transmitter-receiver pairs: one for the client-side signals and the other facing the multiplex section and operating a specific DWDM frequency. Between these is an electrical cross-connect capable of routing signals between the tributary and line side transceivers.

FIG. 8 shows a block diagram of a portion of preferred embodiment of a WDM node for optical rings. Referring to both FIGS. 7 and 8, the transport section generally comprises line cards 805, optical pre-amps 810 and post amps 815, working protect splitter (WPS) section 820, ring switch module (RSM) 825 for performing a line switch.

5 The WPS section 820 preferably is configured to permit working and protect traffic to be demultiplexed. During normal operation (i.e., all fiber lines functional) it is desirable to have the option to transmit data, such as lower priority data, on the protection fibers (i.e., use both the working and protect fibers). WPS section 820 permits data on both working and protection lines to be demultiplexed during normal operation. Additionally, optical  
10 switches are also shown in the WPS section 820 for switching light via the RSM 825. The multiplex section generally comprises band wavelength division multiplexing (BWDM) sections 830 and channel wavelength multiplex division multiplexing (CWDM) sections 835. The transponders 840 (XPND), also known as wavelength converter interfaces (WCIs), correspond to a portion of the tributary sections. There are  
15 redundant BWDM sections 845. The overlapping BWDM and XPND sections illustrate redundant components. Optical switches are included in the CWDM modules to permit a switch to the redundant BWDM modules.

A preferred arrangement of optical detectors is also shown. The pre-amp and post-amplification elements include an inherent ability to determine if they are receiving  
20 optical power. Similarly, the XPND units include an inherent optical signal detection capability. Optical detectors are preferably also included in the WPS and CWDM modules. In the preferred embodiment the BWDM modules do not include optical detectors. The transceiver 850 for receiving OSC signals also includes an optical sensor capability.

A node for dense wavelength division multiplexing (DWDM) may carry a large number of different wavelengths, with each wavelength corresponding to one channel. Consequently, the physical implementation of a DWDM node 400, 500, 700 800 may require a plurality of CWDMs, BWDMs and XPNDs. The components are preferably  
5 arranged on a plurality of field-replaceable circuit packs coupled by short optical jumper links to facilitate a field engineer making rapid field repairs of failed components by swapping circuit packs. FIG. 9 is a block diagram of a partial view of node with field replaceable circuit packs showing a plurality of circuit packs 910 coupled by a local Ethernet connection to at least one OSC/COM module 920. The OSC/COM 920  
10 module contains circuitry for inter-node communication via the OSC channel. The OSC channel may communicate data in a variety of data formats used in digital networks, such as TCP/IP, Ethernet, or ATM format. The OSC links may be configured to form a neighboring node data link. Alternately, data packets may contain address information (e.g., data frames) for transferring data further along the network. Additionally, the  
15 OSC/COM module 920 preferably includes circuitry for coordinating the communication of each circuit pack 910 to an administrative complex 930 corresponding to a microprocessor 940 and memory storage module 950. The OSC/COM module also preferably receives signals from each circuit pack indicative of problems with the circuit pack, such as a loss of electrical power to the circuit pack or internal self-diagnostic  
20 signals from the circuit pack (e.g., an abnormal electrical characteristic indicative of a failed component or a signal from an optical detector residing on the circuit pack).

It will be understood that a software program for performing fault detection and isolation may have slightly different algorithms depending upon the arrangement of optical elements within each node, the number and arrangement of optical sensors for



measuring the optical characteristics of the channels within a node, and the number of elements, such as transponders, capable of providing an output indicative of channel activity. In the most general case a network engineer would analyze the node design and the network topology to produce a “problem list” of likely problems for each signal  
5 indicating a possible loss of a signal channel, plurality of channels, loss of a band, loss of a plurality of bands, or loss of all channels within the node.

Each problem entry in the problem list may have an associated entry describing additional information from other nodes that can be correlated (compared) with the local loss of signal in order to isolate the problem to one or more likely causes. However, in  
10 some cases there may be insufficient information to uniquely isolate the problem to a single cause. In this case, the node may attempt a local solution (e.g., a line switch or an equipment switch) that is the most likely to restore traffic. If the restoration event does not result in a restoration of the dropped channel(s), then this failure may be reported to other nodes (e.g., a list of faulty components published) in order to assist those nodes to  
15 make an appropriate equipment switch or line switch. As an illustrative example, a first node may build a list of potentially failed components within the first node based upon information from a channel map (a list of active channels at various locations in the network) distributed through the OSC and the dropped channel(s) observed by sensors coupled to the first node. The first node may then attempt an equipment switch of one or  
20 more of the components in the its problem list of potentially failed components. If the equipment switch does not restore the dropped traffic (i.e., restore the dropped channel(s)) the node forwards a summary of the failed equipment switch event that may assist other nodes to detect and isolate the problem. For example, the summary of the failed equipment switch event may include a list of dropped channel(s), the components

in the first node suspected of having failed, and the result of the equipment switch (e.g., which of the dropped channels the equipment switch did not restore). An upstream node may, in turn, have a problem list that includes an entry in its problem list instructing the upstream node to initiate an equipment switch in response to several criteria, including

5 initiating an equipment switch if it receives a report that the first node noticed a dropped channel(s) that an equipment switch in the downstream node did not restore. It will be understood that the problem list in the upstream node may also include other criteria for initiating an equipment switch used in combination with the summary of the failed equipment switch, e.g., the problem list of the upstream node may recommend an

10 equipment switch be initiated in the upstream node for the situation that the upstream node receives the summary of a failed equipment switch from the downstream node and one or more other abnormal conditions are detected at the upstream node.

The problem list can be created for a particular node design and arrangement of photodetectors that associates a list of potential problems for various changes in channel

15 status. For each fault listed in the problem list, there is a set of rules for isolating the problem and selecting an appropriate restoration response. This information is preferably encoded as part of a fault detection and isolation program residing on the controller. The fault detection and isolation program correlates system faults and initiates an appropriate restoration action, such as a line switch or an equipment switch. The fault detection and

20 isolation program preferably includes a wavelength management monitor that maintains a list of wavelengths in the network and the status of each channel with respect to source and destination nodes. Status change events are preferably communicated to neighboring (peer) nodes via the OSC. This permits each node to acquire a map of the network topology (e.g., a ring map for a ring network), a channel table of active channels, and to

send or receive path change signals (e.g., send or receive information to neighboring nodes notifying the neighboring node of a line switch event). Thus, each controller keeps a dynamic model of all of the connections to the node, the network topology, the signal paths, and the channel status. The fault isolation program also preferably monitors the

5 optical sensors (e.g, the photodectors in the BWDMs and WPSs), the transponders (WCIs), the OSC channel, and any other photodetectors of the node that may provide information that can be correlated with a fault. The fault correlation program also preferably includes a switch engine that is configured to generate a switch event packet that is forwarded to neighboring nodes via the OSC in order to alert neighboring nodes

10 that a switch event is about to happen. Additionally, the fault correlation program preferably notifies other nodes (e.g., neighboring upstream nodes) if a local equipment switch has failed, thereby providing the other nodes with status information that can be used to make equipment switch decisions.

Table 1 is an illustrative problem list showing signal loss conditions, their likely

15 causes, and suggested fault isolation response. As can be seen in Table 1, information received from the the OSC channel assists the controller of the local node in making equipment switch decisions

Node Condition	Likely Causes	Fault Isolation Response
No OSC signal Received at	1) Line Failure To Neighboring Node Or 2)	1) Initiate Line Switch If There Is Also No optical

OSC detector	Failure of Local OSC Detector	power at Input Buffer. 2) Institute "OSC detector Failure Report" if optical power at input buffer.
No Power At Input Buffer	1) Line Failure between upstream neighboring node, or 2) Line failure upstream of neighboring node;	1) If no OSC signal, initiate ring switch; or 2) if OSC signal present, do not initiate ring switch.
No Power at One Transponder	1) Failure of transponder; 2) dropped channel in node; 3) dropped channel upstream; or 4) channel not presently in operation.	If upstream node reports activity in channel activate equipment switch to elements in node along path of transponder. If problem not solved, report failure to other nodes.
No Power of all CWDMs Linked to a Common BWDM	1) Failure of BWDM; 2) failure of multiple CWDMs; or 3) loss of channels upstream	If upstream nodes do not report a loss of power in affected channels, initiate an equipment switch of BWDM.

Table 1: Illustrative Problem List For An Optical Network

It will be understood that the problem list will depend upon the network topology and node design. FIGS. 10A and 10B are respective portions of a decision table for a

preferred embodiment of the invention for use in an optical ring network. The problem list for typical metropolitan area networks requires comparatively little local memory and computing power, thus facilitating the use of a local controller 430 that is implemented as one or more comparatively low cost microprocessors.

5 Referring again to FIG. 8, it will be noted that some problems are more easily determined than others, depending upon the path of the optical channels through the node relative to the stages in the multiplexor section and on the tributary stage. For example, several transponders are typically coupled to one CWDM. Consequently, a loss in optical output of all of the transponders 840 coupled to a single CWDM may indicate a  
10 failure of the CWDM. However, a loss in optical output of only some of the transponders coupled to the CWDM indicates that a failure of the CWDM is less likely. Similarly, a failure of all of the CWDMs coupled to a BWDM is likely to be caused by a failure of the BWDM, although a failure of a BWDM in another node is also a possibility.

FIG. 11 is a functional block diagram of a preferred fault detection and isolation  
15 system 1100 for implementing the fault detection and isolation function of a local controller 430. The system 1100 preferably includes a fault detector 1110, an equipment switch engine 1120, and a line switch engine 1130. A path signal manager 1140 (shown in phantom) is preferably coupled to software program 1100. Fault detector 1110, equipment switch engine 1120, and line switch engine 1130 are preferably implemented  
20 as software modules of a common software program residing in controller 430. However, it will also be understood that fault detector 1110, equipment switch engine 1120, and line switch engine 1130 may be implemented on separate electrical

components (e.g., separate dedicated circuits or microcontrollers) or reside as software modules on separate microprocessors that are electrically coupled together.

Path signal manager 1140 provides fault detector 1100 with information corresponding to a channel map, i.e., an updated list of all channels that are provisioned at various node locations along the optical network. The path signal manager 1140 is preferably implemented as a software module that resides on the local controller 430 and which receives channel map updates via the OSC channel. However, it will be understood that some of the functionality of path signal manager 1140 may reside in a central monitoring system (not shown in FIG. 11) that accumulates data received from each network node and which publishes channel maps to all of the nodes of the optical network.

The fault detector 1110 is preferably programmed with information corresponding to a problem list 1118, such as a problem list similar to those of FIGS. 10A and 10B, for correlating faults and deciding if an equipment switch or a line switch should be initiated. Fault detector 1110 receives one or more input signals, such as an input signal 1112 from each transponder (WCI) indicating a loss of signal to the WCI port, one or more input signals 1114 corresponding to loss of signal (LOS) from other optical sensors and optical detectors coupled to the local node, and an input signal 1116 corresponding to a circuit pack failure (e.g., an improper electrical connection to one or more of the circuit packs shown in FIG. 9). The fault detector also has a signal input 1111 corresponding to information received from path signal manager 1140. Fault detector 1110 also communicates data on channel activity with path signal manager 1140. Additionally,

The line switch engine 1130 initiates a line switch if it receives trigger signals generated by the fault detector 1110 instructing the line switch engine 1130 to perform a line switch to an alternate optical fiber path. As previously described, the problem list 1118 of fault detector 1110 is preferably programmed such that the fault detector 1110 instructs line switch engine 1130 to initiate a line switch only if there is a loss of signal in both the line-card (e.g., the pre-amp to the node) and the OSC channel. Line switch engine 1130 preferably has a line switch notification output 1132 that informs interested subsystems (e.g., the fault detector within the node and systems in other nodes) that a line switch is complete. A switch engine 1130 that initiates a line switch in response to a trigger signal may be implemented using a variety of conventional line switch engine techniques. For example, switch techniques for optical ring networks are described in U.S. Pat. No. 5,986,783, "Method and apparatus for operation, protection, and restoration of heterogeneous optical communication networks," and U.S. Pat. No. 6,046,833, "Method and apparatus for operation, protection, and restoration of heterogeneous optical networks." The contents of U.S. Pat. Nos. 5,986,783 and 6,046,833 are hereby incorporated by reference in their entirety.

28

administrator. Manual equipment switches are useful to facilitate preventive maintenance or upgrades of node components. Equipment switch engine 1120 may also include a notification signal 1120 communicated to fault detector 1110 and broadcast to other nodes (via the OSC) indicating that the equipment switch is completed.

5           FIG. 12 is an interaction diagram 1200 showing a preferred sequence of interactions for performing an equipment switch using equipment switch engine 1120. Fault detector 1110 instructs equipment switch engine 1120 to perform an equipment switch 1205. Equipment switch engine 1120 issues a sequence of switch commands to switch to redundant back-up components (e.g., WPS/CWDM switches) using a sequence  
10 of switch protocols 1215. The equipment switch engine 1110 then notifies the fault detector 1110 that an equipment switch has occurred 1220, which prompts fault detector 1110 to test if the fault was corrected by the equipment switch. If the results of the equipment switch are a failure, the results of the equipment switch may be published.  
1230.

15           FIG. 13 is an interaction diagram showing a preferred sequence of steps for performing a line switch. A line switch causes a short interruption in network traffic. Consequently, it is desirable for the fault detector 1110 to perform a sequence of steps that are intended to minimize the number of unnecessary line switches. As shown in FIG. 13, the fault detector 1110 continuously receives signal inputs related to potential  
20 faults 1305. If the fault detector 1110 observes an event that may be a line fault the fault detector 1110 performs a step 1320 to see if the node is in the process of being equipment switched and disables the line switch if an equipment switch in progress. In step 1330 fault detector 1110 then confirms that there is no received input power and no signal in



the OSC channel. In step 1340 fault detector 1110 may also verify that the OSC signal detector is not disabled. In step 1350 fault detector 1110 then checks to see if circuit pack card is missing. In step 1360 fault detector 1110 may then check to see if the protection path is operable. The fault detector may then test to see if the OSC signal has  
5 degraded, as shown in 1370, prior to the step of triggering a line switch 1380.

For an arbitrary arrangement of optical components in a node 700, 800 the channels that are supposed to be coupled through each block element may be labeled, permitting, for example, a graph, tree, or table to be prepared showing a list of components in the local node or upstream nodes which could have failed to account for a  
10 loss of specific channels in the local node. A corresponding list of other local node and neighbor conditions for each element in the list may also be generated to further limit the list of components likely to have failed, based upon the information available from the nodes and other information that a field technician can later acquire using conventional field analysis techniques. The microprocessor and persistent memory preferably retains a  
15 history of the detected events and response to the fault. This information is preferably made available (e.g., via a display) to a field engineer along with a list of components likely to have failed and additional action items to confirm which component failed. This information can be in the form of a simple audio visual display (e.g., one or more light emitting diodes or a liquid crystal display) or may be in the form of a numeric code  
20 accessible by the field engineer. Alternately, the information can be presented in the form of a tutorial to guide a field engineer through the steps of an isolation tree. For example tutorial could be presented via a monitor (e.g., a liquid crystal display monitor) coupled to the local node or via a portable computer coupled to the node.

Referring again to FIG. 4, in an alternate embodiment each node may receive information on channel activity from an OSA 440. The use of OSAs 440 increases the cost of the network. However, a benefit of using OSAs is that each node 405 may receive accurate information from the OSA on the channel activity upstream or downstream of the node. A problem list for an embodiment utilizing OSAs 440 would include information coupled to a node 440 by one or more OSAs. In particular, a benefit of using an OSA 440 is that it permits the channel activity of all of the channels to be measured upstream or downstream of a node. This permits an equipment fault to be isolated to a particular node, i.e., to the node where a particular channel or band of channels is dropped. Additionally, the information from an OSA 440 permits the effectiveness of an equipment switch to be determined by a node 405. For example, an OSA 440 downstream of a node may be used to collect information regarding whether an equipment switch instance restored traffic in one or more dropped channels.

While particular embodiments and applications of the present invention have been illustrated and described, it is to be understood that the invention is not limited to the precise construction and components disclosed herein and that various modifications, changes and variations which will be apparent to those skilled in the art may be made in the arrangement, operation and details of the method and apparatus of the present invention disclosed herein without departing from the spirit and scope of the invention as defined in the appended claims.

**CLAIMS****What is claimed is:**

1           1.     An optical node for an optical network transporting an optical datastream,  
2     the node comprising:  
3           at least one port for optically coupling the node to at least one neighboring node;  
4           a fault restoration element to adjust the operation of the node in response to a  
5     fault;  
6           at least one optical sensor for measuring a first set of optical characteristics of the  
7     optical datastream at the node;  
8           a signal sensor configured to receive a second set of optical characteristics of the  
9     optical datastream from an upstream optical device; and  
10          a local controller configured to activate the fault restoration element if the first  
11     and second set of optical characteristics have values corresponding to a potential fault  
12     requiring activation of the fault restoration element.

1           2.     The node of Claim 1, wherein said controller is a microprocessor having a  
2     software program residing on the microprocessor, the software program including a list  
3     of possible faults and corresponding restoration actions as a function of the first and  
4     second set of optical characteristics.

1           3.     The node of Claim 2, wherein said software program records the result of  
2     the restoration instance and communicates the result of the restoration instance to the  
3     optical network.

1           4.       The node of Claim 2, wherein said software program communicates a  
2   message alerting other nodes of optical network of an upcoming restoration instance prior  
3   to the restoration instance.

1           5.       The node of Claim 2, wherein said software program includes a list of  
2   internal components likely to have failed as a function of said first and second set of  
3   optical characteristics, said software program preparing a list of components likely to  
4   have failed for each restoration instance.

1           6.       The node of Claim 1, wherein said restoration element is selected from the  
2   group consisting of: a line switcher, a redundant electrical element, and a redundant  
3   electro-optical element.

1           7.       The node of Claim 1, wherein said upstream device is an optical spectrum  
2 analyzer.

1           8.       The node of Claim 1, wherein said upstream device is an upstream node  
2       having a least one optical sensor residing in the upstream node.

1           9.       The node of Claim 8, wherein the signal sensor is an optical receiver for  
2   receiving status messages via an optical channel, whereby the upstream node  
3   communicates said second set of optical characteristics as a status message via an optical  
4   fiber.

1            10.    An optical node for an optical network, the node comprising:

2           at least one input port for receiving an optical datastream having a plurality of  
3   channels;

4 a plurality of output ports for communicating the data stream to at least one other  
5 node via at least one optical fiber link;

6 a line switcher arranged to select an optical pathway for the data stream between  
7 two of the ports of the node in response to a line switch command;

8           a demultiplexing stage arranged to select at least one channel from said  
9   datastream, said stage including at least one redundant electro-optic element configured  
10   to replace a defective electro-optic element of said stage in response to an equipment  
11   switch command;

12           at least one optical sensor configured to measure a first set of optical  
13   characteristics of the channels;

14 a signal sensor for receiving data from an upstream device on a second set of  
15 optical characteristics of the channels upstream of the node; and

16           a local controller configured to generate the switch commands, the local controller  
17   comparing said first and said second set of optical characteristics to detect a loss of signal  
18   in one or more of the channels, the controller initiating a line switch to isolate a line fault  
19   or an equipment switch to isolate an equipment fault.

1            11.        The node of Claim 10, wherein said local controller comprises a micro-  
2    processor having a software program residing on said micro-processor for generating the  
3    line switch commands and the equipment switch commands, the software program  
4    comparing said first and said second set of optical characteristics against a problem list to

5 determine if a fault has occurred requiring the controller to initiate a line switch or an  
6 equipment switch.

1           12.     The node of Claim 11, wherein said software program includes a fault  
2     detector detecting potential faults as a function of the problem list, a line switch engine  
3     coupled to the fault detector for activating the line switcher in response to instructions of  
4     the fault detector, and an equipment switch engine coupled to the fault detector for  
5     activating the redundant electro-optic element in the node in response to instructions from  
6     the fault detector.

1            13.      The node of Claim 10, wherein the upstream device is an optical spectrum  
2   analyzer.

1            14.    The node of Claim 10, wherein the upstream device is a neighboring node.

1           15.     An optical node for an optical network, the node comprising:

2           a plurality of ports for receiving an optical data stream having a plurality of

3     optical channels and communicating the data stream to at least one other node;

4           at least one fault restoration element to adjust the operation of the node in

5     response to a fault;

6           at least one optical sensor configured to measure a first set of optical

7     characteristics of the channels in the node;

8           at least one transceiver for communicating optical network status information via

9     an inter-node optical communications channel with a neighboring node, the optical

10 network status information including a second set of optical characteristics of the optical  
11 channels determined by sensors residing in at least one other node of the optical network;  
12 a local controller configured to active the at least one fault restoration element if  
13 the first and second set of optical characteristics have values corresponding to a potential  
14 fault requiring activation of the fault restoration element.

1           16.     The node of Claim 15, wherein the optical network status information  
2 includes the publication of a planned line switch or equipment switch in another node and  
3 the local controller is configured to interpret the planned line switch or equipment switch  
4 as a request to not initiate a local line switch command or an equipment switch command  
5 during a time period corresponding to the planned line switch or equipment switch.

1            17.     The node of Claim 15, wherein the optical network status information  
2     includes a channel map of active channels throughout the optical network.

1           18.     The node of Claim 15, wherein said at least one restoration element  
2 includes:

3           a line switcher arranged to select an optical pathway for the data stream between  
4   two of the ports of the node in response to a line switch command; and

5 a demultiplexing stage arranged to select at least one channel from said data  
6 stream, said stage including at least one redundant electro-optic element configured to  
7 replace a defective electro-optic element of said stage in response to an equipment switch  
8 command;

9 wherein the local controller is configured to generate the switch commands, the  
10 local controller comparing said first and said second set of optical characteristics to detect

11 a loss of signal in one or more of the channels, the controller initiating a line switch to  
12 isolate a line fault or an equipment switch to isolate an equipment fault

1 19. An optical node for a wavelength division multiplexing optical network  
2 having an optical datastream with a plurality of optical channels, the node comprising:

3 a transport module, including:

4 a first primary fiber interface port;

5 a second primary fiber interface port;

6 a first secondary fiber port;

7 a second secondary fiber port;

8 at least one input having an optical sensor;

9 at least one output having an optical sensor;

10 at least one transceiver for communicating network channel status  
11 information with at least one neighboring node via an inter-node optical communications  
12 channel; and

13 a line switcher arranged to select an optical pathway between two of said  
14 ports in response to a line switch command;

15 a channel selection module optically coupled to said transport module, said  
16 channel selection module including:

17 a first filter stage containing a demultiplexor element arranged to select a  
18 band of channels from said transport module;

19 a second filter stage coupled to the first stage and arranged to select one  
20 of the channels of said band of channels;





13           a primary optical fiber line linking said first and said second nodes; and  
14           a protection optical fiber line linking said first and said second nodes;  
15           wherein each local microprocessor determines whether to perform a line switch or  
16   an equipment switch as a function of the optical power characteristics of the local node  
17   correlated with the status reports from the other nodes of the optical network via the  
18   inter-node channel.

1            21.    A wavelength division multiplexing optical ring network, comprising:

2           a first node containing a first optical sensor, a first transceiver for receiving and  
3   transmitting data on a first inter-node channel, and a first local microprocessor for  
4   controlling a first line switcher and a first set of redundant electrical elements, the first  
5   local microprocessor transmitting status reports on the optical characteristics of the  
6   channels in said first node via said first transceiver;

7           a second node containing a second optical sensor, a second transceiver for  
8   receiving and transmitting data on the first inter-node channel, a third transceiver for  
9   receiving and transmitting data on a second inter-node channel, and a second local  
10   microprocessor for controlling a second line switcher and a second set of redundant  
11   electrical elements, the second local microprocessor transmitting status reports on the  
12   optical characteristics of the channels in said second node via said second transceiver;

13                   a third node containing a third optical sensor, a fourth transceiver for  
14   receiving and transmitting data on the second inter-node channel, and a third local  
15   microprocessor for controlling a second line switcher and a third set of redundant  
16   electrical elements, the third local microprocessor transmitting status reports on the  
17   optical characteristics of the channels in said third node via said fourth transceiver;

18 a first primary optical fiber line linking said first and said second nodes;  
19 a first protection optical fiber line linking said first and said second nodes;  
20 a second primary optical fiber line linking said second and third nodes;  
21 a second protection optical fiber line linking said second and third nodes; and  
22 at least one additional optical element linking said nodes into an optical ring;  
23 wherein each of the microprocessors determines whether to perform a line switch  
24 or an equipment switch in the node which it resides as a function of the optical  
25 characteristics sensed at the local node and the status reports received from the other  
26 nodes.

1 22. A method of fault detection and isolation in a node of an optical network  
2 having a datastream with a plurality of optical channels, the network including a plurality  
3 of nodes coupled to each neighboring node, each node having at least one local optical  
4 sensor, each node having at least one optical transceiver for communicating status reports  
5 to each neighboring node that it is optically coupled to, and each node having a local  
6 controller for controlling a local line switcher residing in the node, the method  
7 comprising the steps of:

8 sensing a loss in signal from a neighboring node via the local optical sensor;  
9 monitoring the transceiver to determine if the neighboring node is communicating  
10 status reports to the node; and

11 initiating a line switch to redirect traffic to an alternate optical path to restore data  
12 traffic if there is a loss in signal from the neighboring node and status reports are not  
13 being receiving from the neighboring node.

1 23. The method of Claim 22, further comprising the steps of:

2 waiting a preselected period of time to verify a loss of signal; and  
3 initiating a line switch in the node unless a status report is received within the  
4 preselected time.

1 24. A method of fault detection and isolation in a node of an optical network  
2 having an optical datastream with a plurality of channels, the network including a  
3 plurality of nodes optically coupled to each neighboring node, each node having at least  
4 one local optical sensor, at least one transceiver for communicating data to each  
5 neighboring node that it is coupled to, and a local controller for controlling redundant  
6 elements residing in the node, the method comprising the steps of:

7 sensing a first set of optical characteristics of the optical channels traversing the  
8 node;

9 receiving status reports that include a second set of optical characteristics of the  
10 optical channels measured by at least one sensor in another node of the network;

11 comparing the first and second set of optical characteristics;

12 determining if one or more optical channels are being dropped in the node; and

13 initiating an equipment switch in the local node to restore the dropped traffic.

1 25. The method of Claim 24, wherein the second set of optical characteristics  
2 are measured upstream of the node.

1 26. The method of Claim 25, wherein each upstream node includes optical  
2 sensors and the second set of optical characteristics is measured using the optical sensors  
3 of the upstream nodes.



20 selecting an equipment switch decision if a correlation of the channel power  
21 distribution between the node and upstream nodes indicates a likelihood that a failure has  
22 occurred in an electro-optic element in the node;  
23 notifying downstream nodes that an equipment switch will be made; and  
24 activating redundant electro-optic elements in the node.

1 29. A method of fault detection and isolation in a node of a wavelength  
2 division multiplexing optical network comprising a plurality of nodes coupled to each  
3 neighboring node by at least two fibers, each node having at least one local optical power  
4 detector for measuring the power of each channel linked to a local tributary network, at  
5 least one transceiver for communicating data to each neighboring node that it is coupled  
6 to, and a local microprocessor for controlling a local line switcher and redundant  
7 demultiplexing elements residing in the node, the method comprising the steps of:

8 measuring the optical power level of all of the optical channels traversing the  
9 node;

10 measuring the optical power level of at each channel linked to the local tributary  
11 network;

12 receiving reports on the optical characteristics of the optical channels in  
13 neighboring upstream nodes;

14 updating a status list of measured channel characteristics in the node and in  
15 neighboring upstream nodes; and

16 determining if the power level of one of the channels drops below a  
17 predetermined level;

18           waiting a preselected period of time to receive a status update from the upstream  
19 nodes; and  
20           selecting an equipment switch decision if a correlation of the channel power  
21 distribution between the node and upstream nodes indicates a likelihood that a failure has  
22 occurred in an electro-optic element in the node;  
23           notifying downstream nodes that an equipment switch will be made; and  
24           activating redundant electro-optic elements in the node.

1           30.   he method of Claim 29, wherein if a correlation of the channel power  
2 distribution between the node and upstream nodes that a failure is unlikely to have  
3 occurred in the node a signal is transmitted to the upstream node requesting an equipment  
4 switch.

1           31.   The method of Claim 30, further comprising the steps of: determining if  
2 the equipment switch restored power to the dropped channels and notifying neighboring  
3 channels of the result of the equipment switch.

1           32.   The method of Claim 30, further comprising the steps of: forming a list of  
2 components likely to have failed as function of the dropped channels and the result of the  
3 equipment switch; and displaying information indicative of components likely to have  
4 failed.

1           33.   A method of fault detection and isolation in a node of an wavelength  
2 division multiplexing optical network, the node having at least one local optical sensor  
3 for each channel linked to a local tributary network and a local microprocessor coupled

4 to the node for controlling a redundant demultiplexing element of the node, the method  
5 comprising the steps of:  
6 measuring the power level of each channel linked to the local tributary network;  
7 measuring the power levels of a plurality of channels upstream of the node;  
8 comparing the power level of each channel linked to the local tributary network  
9 with the power levels of the channel upstream of the node; and  
10 initiating an equipment switch command sequence if a channel is dropped in the  
11 node.

1 34. The method of Claim 33, wherein the equipment switch command  
2 sequence includes the steps of: notifying downstream nodes than an equipment switch  
3 will be made; and activating redundant electro-optic elements in the node.

1 35. A method of coordinating the action of the nodes of optical network to  
2 perform a fault detection and isolation network function, each node of the network  
3 system status reports between optical network nodes fault detection and isolation in an  
4 each node including at least one local optical sensor for measuring optical characteristics  
5 of the datastream at the local node, at least one transceiver for communicating data to  
6 each neighboring node that it is coupled to via a fiber optic link, and each node having a  
7 local controller for controlling at least one local restoration element, the method  
8 comprising the steps of:

9 sensing a first set of optical characteristics of the datastream at a first node;  
10 updating a channel map of active channels at the first node;  
11 communicating the updated channel map to a neighboring second node via the  
12 fiber optic link;



13           sensing a second set of optical characteristics of the datastream at the second  
14 node; and  
15           comparing the second set of optical characteristics to the channel map to  
16 determine if a fault has occurred requiring that the controller at the second node to  
17 perform activate a restoration element.

1           36.    A method of fault detection and isolation in an optical network having a  
2 plurality of optical nodes, each node including at least one local optical sensor for  
3 measuring optical characteristics of the datastream at the local node, at least one  
4 transceiver for communicating data to each neighboring node that it is coupled to via a  
5 fiber optic link, and each node having a local controller for controlling at least one local  
6 restoration element, the method comprising the steps of:

7           sensing a set of optical characteristics of the datastream at each node;  
8           updating a channel map of active channels at each node of the optical network;

9           and

10          communicating the updated channel map to the nodes via the fiber optic link;

11          wherein each local controller compares the optical characteristics measured at the  
12 local node to the channel map to determine if a fault has occurred requiring that the local  
13 controller activate a restoration element.

# FAULT DETECTION AND ISOLATION IN AN OPTICAL NETWORK

## ABSTRACT OF THE DISCLOSURE

09030301 2634360

An apparatus and method for fault detection and isolation in an optical network is disclosed in which each node determines an appropriate response to a line fault or an equipment fault, obviating the need for a central computer to coordinate the actions of  
5 each node in response to a fault. Each network node includes a local controller and restoration elements for detecting and responding to faults. Each local controller correlates a first set of optical characteristics measured by optical detectors with the local node with a second set of optical characteristics for the channels reported to the local  
10 node from an upstream optical element, such as a neighboring upstream node, to determine if a line switch or equipment switch is required. In a preferred embodiment, each node is communicatively coupled to its neighboring node via an optical supervisory channel, with the neighboring nodes communicating status messages and data on channel characteristics via the optical supervisory channel.

✓ 100






FIG. 1 (prior art)

The diagram illustrates a ring network topology with four nodes labeled NE 1, NE 2, NE 3, and NE 4. The network is divided into Working Bands and Protect Bands. High Priority Circuits are represented by solid lines, and Low Priority Circuits are represented by dashed lines. Each node has a connection 'to NMS'. A handwritten arrow points to the top right corner of the diagram.



400  
↓








FIG. 6







The diagram illustrates a multi-processor system architecture. It is divided into three main sections:

- Administrative Complex (930):** Contains a **Persistent Storage Module (940)** and a **Processor Element Module (950)**. Both modules have two **100BaseTX** ports. The top ports are connected to the **OSC/COM 1** module, and the bottom ports are connected to the **OSC/COM 2** module.
- Transport Complex (910):** Consists of multiple **Circuit Packs (1, 2, ..., n)**. Each circuit pack has two **100BaseTX** ports. The top ports are connected to the **OSC/COM 1** module, and the bottom ports are connected to the **OSC/COM 2** module.
- Oscillator/Communication Modules:**
  - OSC/COM 1 (920):** Receives signals from the top **100BaseTX** ports of the Administrative and Transport complexes. It has two output ports labeled **To Next Shelf Up**.
  - OSC/COM 2 (920):** Receives signals from the bottom **100BaseTX** ports of the Administrative and Transport complexes. It has two output ports labeled **To Next Shelf Down**.

FIG. 9

### Intra-node Fiber Fault Handling

Legend:

RS	Ring Switch
ORS	Ring Switch Delayed
EQ	Equipment Switch
DEQ	Equipment Switch Delayed
LOS	Loss of Signal at receiver(s)

Indicates a resulting action that does not match the desired action for the failure

Component	Connecting Fibre	Local Node Effect: Downstream Node Effect	Desired Protection Action			
			Open Node	Blame passthru	Borrow passthru	RSM Glassthru
Line Postamp	To WPS	If local node adds traffic, downstream neighbor WPS receive PIN detects light. Otherwise, downstream neighbor WPS receive PIN detects no light. Local passthru channels detect LOS downstream. Local add channels are OK downstream	RS	RS	RS	RS
	From WPS	Downstream neighbor WPS receive PIN detects no light. Local passthru or add channels report LOS downstream	RS	RS	RS	RS
	To Unswitched BWDM	If local node adds traffic, downstream neighbor WPS receive PIN detects light. Otherwise, downstream neighbor WPS receive PIN detects no light. Local passthru channels detect LOS downstream. Local add channels are OK downstream	RS	RS	RS	RS
	From Unswitched BWDM	Downstream neighbor WPS receive PIN detects no light. Local passthru or add channels report LOS downstream	RS	RS	RS	RS
PreAmp	To From OSC To Neighbor	Do not protect against OSC failure – use as ring switch trigger if applicable				
	From Neighbor	Downstream neighbor WPS receive PIN detects no light. Local passthru or add channels report LOS downstream	RS	RS	RS	RS
	To WPS or Unswitched Band	If local node adds traffic, downstream neighbor WPS receive PIN detects light. Otherwise, downstream neighbor WPS receive PIN detects no light. Local passthru channels detect LOS downstream. Local add channels are OK downstream	RS	RS	RS	RS
	From Line Card	Downstream neighbor WPS receive PIN detects no light. Local passthru channels detect LOS downstream. Local add channels are OK downstream	RS	RS	RS	RS
WPS	Working from RSM	If local node adds traffic, downstream neighbor WPS receive PIN detects light. Otherwise, downstream neighbor WPS receive PIN detects no light. Local passthru channels detect LOS downstream. Local add channels are OK downstream	RS	RS	RS	RS
	Protect from RSM (No action taken since protect equipment)	Local passthru and add working channels report LOS downstream. PCA channels OK downstream. If local node has protected access traffic, downstream neighbor WPS receive PIN detects light. If no protected access traffic, downstream neighbor WPS receive PIN detects no light	EQ	EQ	EQ	EQ
	Working from backup BWDM	Local passthru and add PCA channels report LOS downstream	n/a	n/a	n/a	n/a
		Only detectable if carrying traffic. If equipment switched, local passthru and add channels report LOS downstream. No autorevert to primary	n/a	n/a	n/a	n/a

None Configured - N/A, Blank, LOS						RSM Glashthru	
Open Node	Pasthru Node	Barne pasthru	Boppsite pasthru				
OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS
OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS
n/a	n/a	n/a	n/a	n/a	n/a	n/a	n/a
n/a	n/a	n/a	n/a	n/a	n/a	n/a	n/a
Downstream OSC LOS LINE IN LOS Action RS	Downstream OSC LOS LINE IN LOS Action RS	Downstream OSC LOS LINE IN LOS Action RS	Downstream OSC LOS LINE IN LOS Action RS	Downstream OSC LOS LINE IN LOS Action RS	Downstream OSC LOS LINE IN LOS Action RS	Downstream OSC LOS LINE IN LOS Action RS	Downstream OSC LOS LINE IN LOS Action RS
OSC LOS LINE IN LOS Action RS	OSC LOS LINE IN LOS Action RS	OSC LOS LINE IN LOS Action RS	OSC LOS LINE IN LOS Action RS	OSC LOS LINE IN LOS Action RS	OSC LOS LINE IN LOS Action RS	OSC LOS LINE IN LOS Action RS	OSC LOS LINE IN LOS Action RS
OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS	OSC OK WPI IN LOS Beam LOS
OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS
OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS	OSC OK LINE IN OK Beam LOS
n/a	n/a	n/a	n/a	n/a	n/a	n/a	n/a
n/a	n/a	n/a	n/a	n/a	n/a	n/a	n/a

Node Configuration - VCC with LDO				
Open Node	Passivhu Node	Buone passivhu	Boppoite	RSM Glassthu
n/a	n/a	n/a	n/a	n/a
n/a	n/a	n/a	n/a	n/a
OSC OK WPS IN OK Result: LOS	OSC OK WPS IN OK Result: LOS	OSC OK WPS IN OK Result: LOS	OSC OK WPS IN OK Result: LOS	OSC OK WPS IN OK Result: LOS
OSC OK WPS IN OK Result: LOS	OSC OK WPS IN OK Result: LOS	OSC OK WPS IN OK Result: LOS	OSC OK WPS IN OK Result: LOS	OSC OK WPS IN OK Result: LOS
Downstream OSC LOS Line in LOS Action: RS	Downstream OSC LOS Line in LOS Action: RS	Downstream OSC LOS Line in LOS Action: RS	Downstream OSC LOS Line in LOS Action: RS	Downstream OSC LOS Line in LOS Action: RS
OSC LOS Line in LOS Action: RS	OSC LOS Line in LOS Action: RS	OSC LOS Line in LOS Action: RS	OSC LOS Line in LOS Action: RS	OSC LOS Line in LOS Action: RS
OSC OK WPS IN OK Result: LOS	OSC OK WPS IN OK Result: LOS	OSC OK WPS IN OK Result: LOS	OSC OK WPS IN OK Result: LOS	OSC OK WPS IN OK Result: LOS
OSC OK Line in OK Result: LOS	OSC OK Line in OK Result: LOS	OSC OK Line in OK Result: LOS	OSC OK Line in OK Result: LOS	OSC OK Line in OK Result: LOS
OSC OK Line in OK Result: LOS	OSC OK Line in OK Result: LOS	OSC OK Line in OK Result: LOS	OSC OK Line in OK Result: LOS	OSC OK Line in OK Result: LOS
n/a	n/a	n/a	n/a	n/a
n/a	n/a	n/a	n/a	n/a

FIG. 10A



```

graph TD
    OSC[OSC] --> PSM[Path signal manager 1140]
    PSM -- 1111 --> FD[Fault Detector 1110]
    FD -- 1112 --> In1[ ]
    FD -- 1114 --> In2[ ]
    FD -- 1116 --> In3[ ]
    FD -- 1119 --> ESE[Equipment switch ENGINE 1120]
    FD -- 1118 --> LSE[LINE SWITCH ENGINE 1130]
    ESE -- 1124 --> Out1[ ]
    ESE -- 1128 --> Out2[ ]
    LSE -- 1132 --> Out3[ ]
    subgraph 1100 [ ]
        PSM
        FD
        ESE
        LSE
    end

```

FIG. 11




FIG. 12




FIG. 13

<b>0016/PTO</b> Rev. 6/95  <b>U.S. Department of Commerce</b> Patent and Trademark Office  <b>DECLARATION FOR UTILITY OR DESIGN PATENT APPLICATION</b>  <input checked="" type="checkbox"/> Declaration Submitted with Initial Filing      OR <input type="checkbox"/> Declaration Submitted after Initial Filing	Attorney Docket Number	<b>5036</b>
	First Named Inventor	<b>Stewart Kevin Hester</b>
	<i>COMPLETE IF KNOWN</i>	
	Application Number	<b>Not Yet Known</b>
	Filing Date	<b>August 23, 2000</b>
	Group Art Unit	<b>Not Yet Known</b>
	Examiner Name	<b>Not Yet Known</b>

As a below named inventor, I hereby declare that:

My residence, post office address, and citizenship are as stated below next to my name.

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled:

**FAULT DETECTION AND ISOLATION IN AN OPTICAL NETWORK**

the specification of which

*(Title of the Invention)*

☒ is attached hereto

OR

☐ was filed on (MM/DD/YYYY) [ ] as United States Application Number or PCT International Application Number [ ] and was amended on (MM/DD/YYYY) [ ] (if applicable).

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment specifically referred to above.

I acknowledge the duty to disclose information which is material to patentability as defined in Title 37 Code of Federal Regulations. § 1.56.

I hereby claim foreign priority benefits under Title 35, United States Code § 119 (a)-(d) or § 385(b) of any foreign application(s) for patent or inventor's certificate, or § 365 (a) of any PCT international application which designated at least one country other than the United States of America, listed below and have also identified below, by checking the box, any foreign application for patent or inventor's certificate, or of any PCT international application having a filing date before that of the application on which priority is claimed.


Prior Foreign Application Number(s)	Country	Foreign Filing Date (MM/DD/YYYY)	Priority Not Claimed	Certified Copy Attached?	
				YES	NO
			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

☐ Additional foreign application numbers are listed on a supplemental priority sheet attached hereto:

I hereby claim the benefit under Title 35, United States Code § 119(e) of any United States provisional application(s) listed below.

Application Number(s)	Filing Date (MM/DD/YYYY)	<input type="checkbox"/> Additional provisional application numbers are listed on a supplemental sheet attached hereto.
<b>60/152,138</b>	<b>08/24/1999</b>	



DECLARATION				Page 2	
<p>I hereby claim the benefit under Title 35, United States Code § 120 of any United States application(s), or § 365(c) of any PCT international application designating the United States of America, listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT international application in the manner provided by the first paragraph of Title 35, United States Code § 112, I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations § 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application.</p>					
U.S. Parent Application Number	PCT Parent Number	Parent Filing Date (MM/DD/YYYY)	Parent Patent Number (if applicable)		
<input type="checkbox"/> Additional U.S. or PCT international application numbers are listed on a supplemental priority sheet attached hereto.					
<p>As a named inventor, I hereby appoint the following attorney(s) and/or agent(s) to prosecute this application and to transact all business in the Patent and Trademark Office connected therewith:</p>					
Name <b>Greg T. Sueoka</b>	Registration Number <b>33,800</b>	Name <b>Edward A. Van Gieson</b>	Registration Number <b>44,386</b>		
<input type="checkbox"/> Additional attorney(s) and/or agent(s) named on a supplemental sheet attached hereto.					
<p>Please direct all correspondence to:</p> <p style="text-align: center;"><b>Edward A. Van Gieson Fenwick &amp; West LLP Two Palo Alto Square Palo Alto, CA 94306 U.S.A.</b></p>					
Telephone	<b>(650) 858-7997</b>		Fax	<b>(650) 494-1417</b>	
<p>I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.</p>					
Name of Sole or First Inventor:			<input type="checkbox"/> A petition has been filed for this unsigned inventor		
Given Name	<b>Stewart</b>	Middle Name	<b>Kevin</b>	Family Name	<b>HESTER</b>
Inventor's Signature				Date	<b>8/23/2000</b>
Residence: City	<b>Belmont</b>	State	<b>CA</b>	Country	<b>USA</b>
				Citizenship	<b>USA</b>
Mailing Address	<b>3619 Hillcrest Drive</b>				
Mailing Address					
City	<b>Belmont</b>	State	<b>CA</b>	Zip	<b>94002</b>
				Country	<b>USA</b>
<input checked="" type="checkbox"/> Additional inventors are being named on supplemental sheet(s) attached hereto					

DECLARATION				ADDITIONAL INVENTOR(S) Supplemental Sheet			
Name of Additional Joint Inventor, if any:				<input type="checkbox"/> A petition has been filed for this unsigned inventor			
Given Name	Todd	Middle Initial		Family Name	Beine	Suffix e.g. Jr.	
Inventor's Signature	<i>Todd Beine</i>				Date	Aug 23, 2000	
Residence: City	Los Gatos	State	CA	Country	USA	Citizenship	USA
Mailing Address	5126 Selinda Way						
Mailing Address							
City	Los Gatos	State	CA	Zip	95032	Country	USA
Name of Additional Joint Inventor, if any:				<input type="checkbox"/> A petition has been filed for this unsigned inventor			
Given Name	Rainer	Middle Initial	Robert	Family Name	Traschko	Suffix e.g. Jr.	
Inventor's Signature	<i>Rainer Traschko</i>				Date	Aug 23, 2000	
Residence: City	Sunnyvale	State	CA	Country	USA	Citizenship	Canadian
Mailing Address	705 San Conrado Terrace, Apt. 3						
Mailing Address							
City	Sunnyvale	State	CA	Zip	94086	Country	USA
Name of Additional Joint Inventor, if any:				<input type="checkbox"/> A petition has been filed for this unsigned inventor			
Given Name	Kent Wilfred	Middle Initial	George	Family Name	Ryhorchuk	Suffix e.g. Jr.	
Inventor's Signature	<i>Kent Wilfred Ryhorchuk</i>				Date	Aug 23, 2000	
Residence: City	Sunnyvale	State	CA	Country	USA	Citizenship	Canadian
Mailing Address	120 E. Remington Drive, #415						
Mailing Address							
City	Sunnyvale	State	CA	Zip	94087	Country	USA
Name of Additional Joint Inventor, if any:				<input type="checkbox"/> A petition has been filed for this unsigned inventor			
Given Name		Middle Initial		Family Name		Suffix e.g. Jr.	
Inventor's Signature					Date		
Residence: City		State		Country		Citizenship	
Mailing Address							
Mailing Address							
City		State		Zip		Country	
<input type="checkbox"/> Additional inventors are being named on supplemental sheet(s) attached hereto							

0064567 003300 22984960